

CONTROL4® CHIME VIDEO DOORBELL



CHIME VIDEO DOORBELL (PoE) C4-VDB-E-xx

CHIME VIDEO DOORBELL (Wi-Fi) C4-VDB-W-xx

Chime is the first video doorbell designed for the Control4 smart home. Chime allows homeowners to see and talk to visitors while controlling the most important smart home features. Customers can see and hear who's at the door through the Control4 mobile app or touchscreen, and a 5MP camera with a 180-degree field of view ensures every inch of the property is covered in crystal-clear HD. Using Composer Pro, you can configure five adjustable motion zones, keeping your customer's most critical areas protected.

Chime also features sensitivity controls to avoid unwanted notifications caused by faraway traffic or passersby. You can trigger a snapshot notification when someone arrives on the porch, or simply set Chime to begin recording without a notification when there's movement in the yard. For additional peace of mind, Chime stores seven days of recordings in the cloud for playback. Chime offers PoE models for new construction or Wi-Fi for retrofit applications and is available in an elegant black or satin-nickel finish to blend in seamlessly with any Control4 smart home.

Feature and benefit highlights

- Video doorbell that fully integrates with Control4 smart home
- 5MP HD camera with 180-degree field of view
- Two-way audio, no push and release required
- Five customizable motion zones with sensitivity control
- Night mode and IR LEDs
- Stores seven days of event recordings in the cloud
- Wi-Fi and PoE models
- Available in black and satin-nickel finishes

CONTROL4® CHIME VIDEO DOORBELL

Features

Complete smart home control

No other video doorbell delivers a complete smart home experience like Chime. While communicating with someone at the front door, homeowners can simultaneously disarm the alarm, unlock the door, open the garage door, or any other smart home features you can imagine. Homeowners can also communicate with others inside the house both at home or on the go with the help of their touch screen or mobile app.

Program customized scenes

With your help, buttons on the Control4 app or touchscreen can initiate a series of smart home events. If someone the homeowner knows arrives at the door, a single push of a button will disable the alarm, let them inside, and turn on the lights. You can also set the camera to start recording automatically when it senses movement on the porch or in the driveway.

See and hear clearly

A 5MP HD camera promises sharp video quality, and night mode and IR LEDs offer clear visibility, even in low light. Chime even features a 180-degree field of view for monitoring that goes well beyond the front door. Plus, two-way audio allows for natural conversations—no push and release required.

Adjustable motion zones and sensitivity controls

Personalize up to five motion zones with customized sensitivity control to ensure homeowners are notified when it matters most. Program Chime to send a notification with a camera snapshot whenever someone steps onto the front porch, or start recording without a notification when there's movement in the yard. Or, set a scene that turns on the garage light and starts recording when there's movement in the driveway after midnight. With Chime, the options for customization are endless.

Stylish and strong

Available in black and satin nickel finishes, Chime features a stylish design that blends seamlessly into any upscale smart home. Plus, Chime is IP65 rated and water resistant to keep it looking new for years to come.

Pro-grade features

Chime is available in Wi-Fi and PoE models, so it can be installed in retrofit jobs or new construction. Configuration is easy with the help of Composer Pro, which lets you program motion zones, custom alerts, snapshots, brightness levels, LEDs, and more.

Install peace of mind

Chime automatically stores seven days of recordings, and OS 3 lets you go back and watch video clips from the Control4 mobile app or touchscreen. In addition to seeing what happened at the front door, you can also access a History view of what happened in the home throughout the day. For increased video storage, pair Chime with a Luma NVR.

Remote monitoring and management

Service Chime from anywhere in the world with OvrC remote management. Receive notifications if there's an issue with your customer's system and get them back up and running fast from an easy-to-use mobile or web app.



CONTROL4® CHIME VIDEO DOORBELL




	<u>Model</u>	<u>Chime Video Doorbell (PoE)</u>	<u>Chime Video Doorbell (Wi-Fi)</u>
	<u>Model numbers</u>	C4-VDB-E-SN (satin nickel) C4-VDB-E-BL (black)	C4-VDB-W-SN (satin nickel) C4-VDB-W-BL (black)
	<u>Video</u>		
	<u>Camera resolution</u>	5MP	5MP
	<u>Video resolution</u>	Main: up to 1600 × 1200 Substream: up to 1024 × 768	Main: up to 1600 × 1200 Substream: up to 1024 × 768
	<u>Frames per second</u>	Up to 24 FPS	Up to 24 FPS
	<u>Video substream</u>	Y	Y
	<u>Video codec</u>	H.264 or MJPEG	H.264 or MJPEG
	<u>Night mode</u>	Integrated IR LEDs for night mode	Integrated IR LEDs for night mode
	<u>Aspect ratio</u>	4:3, nearly 180-degree horizontal FoV	4:3, nearly 180-degree horizontal FoV
	<u>Motion detection</u>	5 configurable motion zones	5 configurable motion zones
	<u>Audio</u>		
	<u>Mic</u>	Built-in omnidirectional	Built-in omnidirectional
	<u>Speaker</u>	Y	Y
	<u>Codec</u>	G.711	G.711
	<u>Mechanical</u>		
	<u>Dimensions (H × W × D)</u>	130 × 40 × 28 mm (5.12 × 1.58 × 1.10 in.)	130 × 40 × 28 mm (5.12 × 1.58 × 1.10 in.)
	<u>Weight</u>	159 g (0.35 lb)	136 g (0.30 lb)
	<u>Available colors</u>	Satin Nickel Black	Satin Nickel Black
	<u>Mechanical chime support</u>	Yes	Yes (with adapter)
	<u>Power</u>		
	<u>Power source</u>	PoE 802.3af	16-24V
	<u>Environmental</u>		
	<u>Operating temperature</u>	-40 °C to 60 °C (-40 °F to 140 °F)	-40 °C to 55 °C (-40 °F to 131 °F)
	<u>Storage temperature</u>	-45 °C to 70 °C (-49 °F to 158 °F)	-45 °C to 70 °C (-49 °F to 158 °F)
	<u>Humidity</u>	20% to 100% RH (non-condensing)	20% to 100% RH (non-condensing)
	<u>Outdoor rating</u>	IP65	IP65
	<u>Accessories</u>		
	<u>Jbox</u>	C4-VDB-JBOX 1/2 Gang Junction Box	N/A
	<u>FOV Wedge and Backplate</u>	C4-VDB-E-ACC contains a 15-degree left and right wedge and wall plate	C4-VDB-W-ACC contains a 15-degree left and right wedge and wall plate
	<u>Certifications</u>	FCC class B, CE, IC	FCC class B, CE, IC


CONTROL4® CHIME VIDEO DOORBELL



**C4-VDB-E (PoE)
template**



**C4-VDB-W (Wi-Fi)
template**




LATEST VERSION OF THIS DOCUMENT




ctrl4.co/chime-ds

INSTALLATION GUIDE, POE



ctrl4.co/chime-e-ig

INSTALLATION GUIDE, WI-FI



ctrl4.co/chime-w-ig